

**Package Include:**

1\* Receiver (with cover)

1\* Remote Control (with battery, If you need extra remote control , please tell us. )

**If you have any questions, please contact us**

**Service E-Mail: [sale@einausschalten.com](mailto:sale@einausschalten.com)**

**Tel: +86 183 2644 0199**

- Application: Pumps, Mud Pumps, Motors, Lamps, Fans, Fans, Insecticide Machines, Sprayers, Car Washers, Bells, etc. Various types of electrical equipment (for home use, power up to 3,000 watts Electrical appliances).
- Wireless control, easy to install. The wireless receiving controller, with high confidentiality, stable performance, low power consumption characteristic, jump line or dial the code switch coding.
- Wireless RF signal can pass through walls, floors, doors or windows. You can use two or more units in the same place. You can turn on/ off the receiver with transmitter (remote control) from any place within a reliable distance.
- Reliable control: The receiver only works with the transmitter which use same code. One/several transmitters can control one/several receivers simultaneously. High Power: Each channel can work at maximum current 30A, Do not need AC contactors, direct control of water pumps, motors, lamps, car washers, etc. within 3000W
- High sensitivity:RXB8 module, sensitivity -114dBm, sensitivity and anti-jamming capability are far beyond super-renewable and ordinary superheterodyne modules on the supermarket, and the remote control distance is farther and more stable.

**Product Description**

Working Voltage : 85V-250V

Output Current : 30A

Rated power: 3000W

Working Frequency : 315 MHz( Frequency can be customized)

Receiver sensitivity: : -114dBm (RXB8 Modul)

Working temperature : -10°C - +60°C

Code type :Learning code

Receiver size: 123\*61\*30.5mm

Cable length of antenna: 3m

Range: 1000-3000M (We actually tested 2360 meters.)

**Control mode Description**

Toggle (1 button on / same button off)

Latch (1 key on / other key off)

Momentary (Press and hold -> On; Release -> Off)

**Set the control mode**

Toggle: Turn 1of the dip switch not to ON, 2 to ON.

Momentary: Turn 2 of the dip switch not to ON, 1 to ON.

Latch: Turn 1 and 2 of the dip switch not to ON.

Learning method: Turn on the power, Receiver light will light for 3 seconds, After it is extinguished, press the learning button briefly. The indicator light is on. Press the remote control button immediately. The indicator light will turn off. Learning success

Clear code: Turn on the power, Receiver light will light for 3 seconds, After light extinguishing, press and hold the learning button of the receiver. The indicator light is on. After eight seconds, the indicator light flashes three times and goes out. The clear code is successful.

Tip:

1: The theoretical control power is 6600W, because the load starts current, so it is not recommended to exceed 3000W

2: The hand transmitters have a range in the open area of about 2500m. Constructions, interfering radiation and interference fields reduce the range.

Service:

E-Mail: [sale@einausschalten.com](mailto:sale@einausschalten.com) Tel.: +86 183 2644 0199



