

If you have any questions, please contact us
Service E-Mail: sale@einausschalten.com
Tel: +86 183 2644 0199

Specifications:

Control Lights, TVs, Motors, Fans, Cameras, Video signals, Audio signals, electrically operated Doors/ Locks/ Windows.

1. Transmitter

Channel: 16 CH

Remote Control Distance: 0-100 M

Encode: PT2262

Frequency: 315 or 433 MHz

Size: 130mm x 52mm x 13mm

Power Supply: 1 X 12V/23A Battery (NOT included)

2. Control Mode

1) 1-16 Toggle/Self-lock : Press 1 button ==> on, press the same button again ==> off (Press key 1 to learn)
press key 1, 1 relay works, press key 1 again, 1 relay stops working. press key 2, 2 relay works, press key 2 again, key 2 stops working. 3-16 key works like this.

2) 1-16 Momentary/Jog: Press and hold ==> on, release ==> off (Press key 2 to learn)
press key 1 and hold, 1 relay works, loosen the finger. 1 relay stops working. 2-16 key works like this.

3) 1-16 Latched/inter-lock: press 1 button ==> on, press other button ==> off (Press key 3 to learn)
press key 1, 1 relay works, press key 2, 1 relay stops working, 2 relay works. 3-16 key works like this.

4) 1-8 Toggle 9-16 Momentary (Press key 4 to learn)

5) 1 Toggle 2-16 Momentary (Press key 5 to learn)

(Original Setting is Momentary, change it by yourself.)

Decode: Fixed code, soldering

Power Supply (Operating Voltage): DC 12V / 24V

Current: 8 mA

Sensitivity: -105 dBm

Operating Temperature: -20°C - 70°C

Size: 117 X 74 X 18 mm

3. Package Included

1 x Receiver (with cover)

1 Transmitter (with battery)

4. Learn code and Clear Code

1). Clear code: Press the learning button on the receiver about 10 seconds, when hear BI sound again, it means the codes are cleared.

2). Press the learning button on the receiver for one time, when hear BI sound, it means enter into learning status, then press the relative button on the remote, when hear 3 sounds BI BI BI, it means learn successfully.



