

## 110V 220V 250V 3000W RF Wireless Remote Control Lighting Switch System With Transmitter For Smart Home 30A high power

Package Include:

- 1 x Receiver:(with cover)
- 2 x Transmitter: (with battery)

Item specifics

Item Type:Switches  
Remote Distance:10-100M  
Warranty:1 year  
Features:Input=Output  
Certification:CCC  
Switch Type:Remote Control  
Max. Voltage:85-250V  
Max. Current:30A  
Operating Temperature:-20'C~+60'C  
Encoding type:Learning Code  
Learning Code :315/433MHZ

Product Description

- 1.Working Voltage: AC85-250V
  - 2.Max Load:30A Relay, Resistive load $\leq$ 25A, Inductive load $\leq$ 20A
  - 3.Channel: 1CH
  - 4.Working Frequency : 315MHZ/433.92MHZ Optional
  - 5.Receiver sensitivity: : -105Db
  - 6.Working temperature : -20'C - +60'C
  - 7.Output way : Momentary. Toggle .Latched Adjusted by Jumper
  - 8.Code type: Learning code Add Controller by the Learning Button on the receiver
  - 9.PCB Size : 70\*50\*18mm
  - 10.Standby current :10MA
- Output State:

It is adjusted by the Jumper on the Receiver Board,

- A: Momentary-----Put the Jumper on 1 Pin or take away the Pin  
B: Toggle-----put the Jumper on "1&2"  
C: Latched----- Put the Jumper on "2&3"

Momentary-----Press the Transmitter button A, the receiver relay A is ON, release button A; the receiver relay A is OFF,

Toggle-----Press transmitter button A for 1 time , the receiver relay A is ON, press button A again, the receiver relay A is OFF,

Latched-----Press transmitter button A, the receiver relay A is ON, Press transmitter button B, the relay A OFF.

Learning Code

Input AC220V for the Receiver ,the receiver power indicator ON, Press the Learning Button until the Led indicator OFF. Then press transmitter, the Led indicator flash for 3 times, it mean learning successfully.

Clearing Code

press the Learning Button and hold, the LED indicator from OFF to ON, it means clearing is successfully.

