

Important Note:

Non professionals please don't buy this relay module.

Packing List:

- 1 X IR switch module
- 1 X IR remote (no battery)

Product Introduction:

1 Working voltage: 5V DC
Remote control power supply: A CR2025 button battery

2 VIN+: Connect with 5V + GND: Connect with 5V -
CK=normally open, COM=common, CB=normally close, all of these three ports connect with output.

3 Module Dimension: 50*40*20mm, with four fixed 3mm-bolt holes

4 Module Type: IR remote switch

5 Receiver Distance: 3-8 m

6 Working Mode: Self-lock control

How the remote work?

- 1 Press the CH1 once time, then the 1st channel on the module will be closed. Press the CH1 again, then the 1st channel on the module will be released.
- 2 Press the CH2 once time, then the 2nd channel on the module will be closed. Press the CH2 again, then the 2nd channel on the module will be released.
- 3 Press the power button once time, then the two channels on the module will be closed. Press the power button once more time, then the two channels on the module will be released.

Tips:

- 1 The receiver module must be matched with our remote, usually it does not work with other wireless remote.
- 2 The receiver module provides electrical isolation CK and CB connectors.
- 3 The receiver module works with 250VAC-10A, 125VAC-10A, 30VDC-10A, 28VDC-10A Load, it works for most home appliances, garage and other machine