

**Important Note:**

Non professionals please don't buy this relay module.

**Packing List:**

1 X 12V IR relay module  
1 X IR remote(inkl. battery, can use 6 month )

**Product Introduction:**

Working voltage: 12V DC

Remote control power supply: A CR2025 button battery

VIN+: Connect with 12V+ GND: Connect with 12V-

CK=normally open, COM=common, CB=normally close, all of these three ports connect with output.

Module Dimension: 50\*20\*20mm

Quiescent current: <1ma

A Module Type: IR remote module

Receiver Distance: 8 meter

Working Mode: Self-lock control (Press the button on remote, then relevant Channel of the relay module will work. press the button once again, then it will stop)

**How the remote work?**

Supply power to the module. Press "ON" button, the relay is closed(COM and CK is connected), the LED light will be on. Press "OFF" button, the relay is released. (COM and CB is connected), the LED light will be off.

**Tips:**

1 The receiver module must be matched with our remote, usually it does not work with other IR remote control.

2 The receiver module provides electrical isolation CK and CB connectors.

3 The receiver module works with 250VAC-10A, 125VAC-10A, 30VDC-10A, 28VDC-10A Load, it works for most home appliances, garage and other machine

