

Important Note:

Non professionals please don't buy this module. This switch module must work with our remote control.

Packing List:

- 1 X 8-way 12V IR Self-lock Switch module
- 1 X 5-key IR remote

Product Introduction:

1 Working voltage: 12V DC

Remote control power supply: A CR2025 button battery

2 VIN+: Connect with 12V+ GND: Connect with 12V-

CK=normally open, COM=common, CB=normally close, all of these three ports connect with output.

3 working current: less than 250mA

4 static working current: less than 5mA

5 Module Dimension: 91*66*20mm, with four fixed 3mm-bolt holes

6 Module Type: IR remote module

7 Receiver Distance: 3-8m

8 Working Mode: Self-lock control (Press the button on remote, then relevant Channel of the relay module will work. press the button once again, then it will stop.)

How the remote work?

1 Press the CH1 button once time, then the CH1 channel on the module will be closed. Press the CH1 button on more time, then the CH1 channel on the module will be released.

2 Press the CH2 button once time, then the CH2 channel on the module will be closed. Press the CH2 button on more time, then the CH2 channel on the module will be released.

The same with other CH3, CH4, CH5, CH6, CH7, CH8 button.

3 Press the power button once time, then the four channels on the module will be closed. Press the power button once more time, then the four channels on the module will be released.

Tips:

1 The receiver module must be matched with our remote, usually it does not work with other wireless remote.

2 The receiver module provides electrical isolation CK and CB connectors.

3 The receiver module works with 250VAC-10A, 125VAC-10A, 30VDC-10A, 28VDC-10A Load, it works for most home appliances, garage and other machine

