

Mini RF DC3.7V to 24V 2 Relay Wireless Remote Control Switch 12v Learning Controller 433mhz Receiver +Transmitter

Item specifics

Package:Yes

Frequency:433 MHz

Channel:2

Use:Universal

remote control size:2.31inch*1.51inch*0.53inch

The battery model of remote control:23A 12v

module size:0.87inch*0.81inch*0.44inch

Standby current:7mA

Single way working current:60mA

Load power:1A(Less than 5 watts)

Power supply module:3.7V to 24V

Control Distance:200m open environment, Can be used through walls

Product frequency:433mhz

The customer diy:Suitable for the customer DIY

Product preponderance

1.360 degree,NO dead Angle

2.RF Remote Control Switch,can through walls

3.Ultra low power,High sensitive response

4.Super small size,Factory direct sale

5.Independent coding, many sets will be not interference of each other

Products use instructions

The controller output switch node in the 2 groups(ON and COM)

Belong to switch on and off the line type, Not the output power

Used for on-off control circuit, Wire and wire connection, Inching button

Product parameters

Working voltage: DC 3.7V to 24V (Wide voltage general)

Module dissipation: 7mA

Product frequency:433MHZ

Load power: 1A(Less than 5 watts of equipment)

Module size: 0.87inch*0.81inch*0.44inch

Remote control size: 2.31inch*1.51inch*0.53inch

Remote control distance: open environment of distance about 200M,Can be used through walls

Product wiring instructions.

The output is 2 set of contact switch module, Standby mode, Two way switch is disconnected.

Article 2 yellow wire, 2 blue wire, is an independent switch 2 groups,

press the remote control button, Two groups switch work at the same time, loosen the remote control button, 2 set of switch off at the same time

Product wiring instructions

