

RF Mini 433mhz Wireless 2 Relay Remote Control Switch 12v Micro Receiver DC3.7v to 24v home office

Item specifics

Package:Yes

Frequency:433 MHz

Channel:2

Use:Universal

The battery model of remote control:23A 12v

module size:0.87inch*0.81inch*0.44inch

Standby current:7mA

Single way working current:60mA

Load power:1A(Less than 5 watts)

Power supply module:3.7V to24V

Control Distance:200m open environment, Can be used through walls

Product frequency:433mhz

remote control button:3 button A B D

Product features

- 1.360 degree,NO dead Angle
- 2.RF Remote Control Switch,can through walls
- 3.Ultra low power,High sensitive response
- 4.Super small size,Factory direct sale
- 5.Independent coding, many sets will be not interference of each other
- 6.If need more set of general,please descr

Products use instructions

the first set of switch control A button(two Blue wire)

the second set of switch control B button(two Yellow wire)

The controller output switch node in the 2 groups(ON and COM)

Belong to switch on and off the line type, Not the output power

Used for on-off control circuit, Wire and wire connection, Inching button

Product parameters

Working voltage: DC 3.7V to 24V (Wide voltage general)

Module dissipation: 7mA

Product frequency:433MHZ

Load power: 1A(Less than 5 watts of equipment)

Module size: 0.87inch*0.81inch*0.44inch

Remote control distance: open environment of distance about 200M,Can be used through walls

Control Mode Description

Latch (1 key on / other key off)

Momentary (pushbutton function, relay moves as long as button is pressed)

Note: This control mode can not be set, so you must confirm the appropriate control mode before purchasing.

use

Momentary:

Press button A, close two yellow cables, release button A, relay 1 is disconnected.

Press B, two blue cables close, release button B, relay 2 is disconnected.

Press the D button, two groups of switches close simultaneously.

Leave the button free, two groups switch disconnect at the same time.

latch:

Press the A button, close two yellow cables, press D, is disconnected.

Press the B button, two blue cables close, press D, is disconnected.

Note: Two groups of switches can not simultaneously turn on at control mode latch, that is, when a relay turns on, other relays are turned off.

Product wiring instructions

