

**Important Note:**

Non professionals please don't buy this relay module.

**Packing List:**

1 X IR relay module  
1 X IR remote control

**Product Introduction:**

Working voltage: 5V DC

Remote control power supply: A CR2025 button battery

VIN+: Connect with 5V + GND-: Connect with 5V -

CK=normally open, COM=common, CB=normally close, all of these three ports connect with output.

Module Dimension: 50\*20\*20mm

Quiescent current: < 1ma

AModule Type: IR remote module

Receiver Distance: 8 meter

Working Mode: Self-lock control (Press the button **ON** on remote, then relevant Channel of the relay module will work. press the button **OFF**, then it will stop)

**Tips:**

1 The receiver module must be matched with our remote, usually it does not work with other IR remote control.

2 The receiver module provides electrical isolation CK and CB connectors.

3 The receiver module works with 250VAC-10A, 125VAC-10A, 30VDC-10A, 28VDC-10A Load, it works for most home appliances, garage and other machine

**Notice:**

We will send you a whole receiver port. You can tailor this receiver port to your requirements. When installing, you must set this receiver port to hole from the top or side part, otherwise receiver efficiency will be impaired. If you cut this receiver port, you should first select the appropriate length and then cut it. Please make step by step. You can not cut times as long.

